

Vista MSC Command Reference

Example: F0 7F [Device_ID] 02 01 [Command] [Data] F7

MSC Command	Action	Data Option		ID		CMD	Data		Result
01 GO	Go	Cue*, Cuelist	F0 7F	01	02 01	01		F7	
02 STOP	Pause	Cue*, Cuelist	F0 7F	01	02 01	02		F7	
03 RESUME			F0 7F	01	02 01	03		F7	
04 TIMED_GO	Go with Time	Cue*, Cuelist, Time	F0 7F	01	02 01	04		F7	
05 LOAD									
06 SET									
07 FIRE	Load Snapshot		F0 7F	01	02 01	07		F7	
08 ALL_OFF	GM to Zero		F0 7F	01	02 01	08		F7	
09 RESTORE	Reverse All_Off	Cue*, Cuelist	F0 7F	01	02 01	09		F7	
0A RESET	Release All		F0 7F	01	02 01	0A		F7	
0B GO_OFF	Release Cuelist	Cuelist	F0 7F	01	02 01	0B		F7	
10 GO/JAM_CLOCK		Cue*, Cuelist	F0 7F	01	02 01	10		F7	
11 STANDBY_+									
12 STANDBY_-									
13 SEQUENCE_+									
14 SEQUENCE_-									
15 START_CLOCK	Start Internal TC		F0 7F	01	02 01	15		F7	
16 STOP_CLOCK	Stop Internal TC		F0 7F	01	02 01	16		F7	
17 ZERO_CLOCK	Set Internal TC to 0		F0 7F	01	02 01	17		F7	
18 SET_CLOCK	Set Internal TC value		F0 7F	01	02 01	18	04 0A 1A 18	F7	04:10:26:24
19 MTC_CHASE_ON			F0 7F	01	2 01	19		F7	
1A MTC_CHASE_OFF			F0 7F	01	2 01	1A		F7	
1B OPEN_CUE_LIST		Cuelist	F0 7F	01	2 01	1B		F7	
1C CLOSE_CUE_LIST		Cuelist	F0 7F	01	2 01	1C		F7	
1D OPEN_CUE_PATH									
1E CLOSE_CUE_PATH									

TC Number Data			
#	Hex	#	Hex
0	00	31	1F
1	01	32	20
2	02	33	21
3	03	34	22
4	04	35	23
5	05	36	24
6	06	37	25
7	07	38	26
8	08	39	27
9	09	40	28
10	0A	41	29
11	0B	42	2A
12	0C	43	2B
13	0D	44	2C
14	0E	45	2D
15	0F	46	2E
16	10	47	2F
17	11	48	30
18	12	49	31
19	13	50	32
20	14	51	33
21	15	52	34
22	16	53	35
23	17	54	36
24	18	55	37
25	19	56	38
26	1A	57	39
27	1B	58	3A
28	1C	59	3B
29	1D	60	3C
30	1E		

Cuelist Number Data	
#	Hex
0	30
1	31
2	32
3	33
4	34
5	35
6	36
7	37
8	38
9	39
.	2E

*Include 00 between Cue and List number. If list number is not specified, default list will be triggered.